

Bron-y-Gader Fire Alarm Testing

1. First check that the panel is in the normal active state.

The only light that should be lit is the green 'supply present' lamp.

If that is not the case, refer to the "Fire Alarm Fault Procedure" (in the folder).



2. Insert the red plastic key (on chain below the panel) and turn to the 'I' position. The 'accessed' light will turn on.



3. Press the 'lamp test' button (button 4) to test the panel lights. The panel lights should light up as shown right. Note: only Zones 1 and 2 will light as there are only 2 zones in operation.



4. Press the 'silence/resound sounders' button (red surround) to test the fire bells/sounders. Walk through the building to check all 3 bells/sounders are working (in large hall, top of stairs and upper bedroom corridor).
5. Press the 'silence/resound sounders' button to silence the sounders.



6. Press the 'control panel reset' button to put the panel back to normal state.
7. Turn the key to 'O' and remove.

If any faults are found, refer to the "Fire Alarm Fault Procedure" (in the folder).

